



MAS INTERCOM

BERGAMA COMPACT DOORPHONE

PRODUCT SPECIFICATION

BT01C

- The contact under the handset is not mechanic but magnetic. This decreases frequent breakdowns of the device.
 - Anti-block system : if for any reason the handset remains off hook, the device resets itself and avoids the system to stay in “occupied” state.
 - Easy mount and connection : Once the back plate is fixed to the wall, the handset can be tested and replaced without any need to dismount the cables.
 - Two doorbell melodies to distinguish where the visitor is (at building or apartment door)
 - The melody “ding-dong” is generated by an electronic circuit whilst in most part of handsets in the market, this ring comes from a buzzer (vibrating relay)
 - Private communication : if a handset is in communication with the outdoor panel, no other handset can enter into communication.
 - The cable of the handset has a removable connector and this gives the possibility to change the cable in case of a breakdown without opening the device.
 - The outdoor panel is not made of metal-coated plastic but fully in aluminum. Same for buttons.
 - After dark, a white LED lights the names on the buttons of the outdoor panel.
 - For outdoor panels having more then one button, a red LED is lighting a button whenever it is pressed.
-
- Operating Voltage: 12VDC
 - Power: 3A
 - Dimensions: 200x100x30 mm
 - Weight: 0.35 kg
 - Approvals: CE, GOST
 - Operating Temperature: 40 ~ 120 F (5 ~ 50°C)



TERMINAL DEFINITIONS OF BERGAMA DOORPHONES WITH DOORBELL

- 1.Voltage input for doorphone (+)
- 2.Voltage input for doorphone (-)
- 3.Triggering voltage input for doorbell (1st melody)
- 4.Triggering voltage input for doorbell (2nd melody)
- 5.Voice signal input
- 6.Voice signal output
- 8.Output-2 of inner contact